



THE KORG MICROKORG PATCH FILES

Before starting you must have a TO and FROM MIDI connection between your computer and the MicroKorg. The following instructions are not meant to replace the user manual or any included help files. Please consult your documentation.

Any software that is made available on the DVD-ROM, including any files, images incorporated in or generated by the software, and data accompanying the software (collectively, the "Software"), are the copyrighted work of Producer's Edge or other indicated author of the Software ("Author"). Use of the Software is governed by the terms of the end user license agreement, if any, which accompanies or is included with the Software ("License Agreement"). An end user will be unable to install any Software that is accompanied by or includes a License Agreement, unless he or she first agrees to the License Agreement terms. The Author retains full and complete title to the Software itself, and all intellectual property rights therein. You may not redistribute, sell, decompile, reverse-engineer or otherwise disassemble the Software. OWNER MAKES NO WARRANTY AS TO THE QUALITY OF SUCH SOFTWARE INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

*The ability to transmit and receive MIDI-data is not exclusive to MIDI-OX, it is merely used here as an example.

A) Setting up MicroKorg to receive Program Data

You must first turn off the MicroKorg Write Protect. If you have custom patches you want to save, please back-up your current patch data as this bulk dump will overwrite all the internal programs. See (C) for Dumping Data FROM the MicroKorg if you want to save your custom patches first.

Hold down Shift key and Press 8. The display reads GtP. Turn the 1 knob to switch Write Protect OFF. Press 8 again to execute.

B) Setting up MIDI-Ox to SEND DATA to the MicroKorg

View/SysEX

Load File (0 Producers Edge Bank 01 SYSEX) from DVD-ROM using Browser
Choose Send Sysex

C) Setting up MIDI-OX to receive a MIDI DUMP from a sound Module

Choose

VIEW/SysEX

Sysex/Receive Manual Dump. Dump DATA from MicroKorg by holding down shift and pressing 6. The display will indicate daP. Turn knob 1 to select type of

data to be dumped. 1 program (1Pg) All Programs (Pr9) or (GLb) global settings. (All) for both Global and Programs. Press 6 to execute.

D) Resetting the Factory DATA of the MicroKorg

You must first turn off the MicroKorg Write Protect. If you have custom patches you want to save, please back-up your current patch data as this bulk dump will overwrite all the internal programs. See (C) for Dumping Data FROM the MicroKorg if you want to save your custom patches first.

Hold down Shift key and Press 8. The display reads GtP. Turn the 1 knob to switch Write Protect OFF. Press 8 again to execute.

Hold down Shift key and press 7. The display reads PLd. Turn knob 1 to select a single program (1Pg) or data for All Programs (Pr9). Press 7 to execute

Griffin Avid



<http://www.korg.com/gear/>